

CC45WD OSD MENU



Press the center Button to Enter the OSD Menu.
 Move Up or Down to move thru the menu options and left or right to change values on the menu,
 Press the center button again to get into sub menus.
 Always remember to save before you exit.



1. CAM NAME

| | | | | |
|-----|-----------------|--|--|-----------------------------|
| OFF | | | | type the name of the camera |
| ON | < CAMERA NAME > | | | |
| | ABCD.....XYZ | | | |
| | 123.....89 | | | |
| | <-> CLR POS END | | | |

2. LENS

| | | | | |
|---------|--------------------|--|--|---|
| MANUAL | | | | Select from Manual or DC Iris Depending on the lens used to this camera. |
| DC IRIS | DC IRIS MENU | | | |
| | BRIGHTNESS (0~100) | | | |
| | PREVIOUS | | | |

3. EXPOSURE

| | | | | |
|---------------|------------------------------|----------|----------------------------|---|
| EXPOSURE MENU | | | | Exposure Settings: AGC (Automatic Gain Control) settings Set the Shutter speed according to the environment. (SENSE-UP) AFLK (Manual Speed Setting) |
| AGC | OFF / LOW / MIDDLE / HIGH | | | |
| SHUTTER | OFF | | | |
| | AFLK | SENSE UP | AUTO x2 / AUTO x 512 / OFF | |
| | (1/160 ~ 1/90000) (x512~x2) | | | |
| | AUTO | SENSE UP | AUTO x2 / AUTO x 512 / OFF | |

4. DAY/ NIGHT

| | | | |
|-------|-------------|--------------------|---|
| AUTO | D/N LEVEL | LOW/ MIDDLE / HIGH | IR Filter Setup Filter DEL - Adjustable Filter Delay in sec. Night burst - help lighten up the overall image when it goes into |
| | FILTER DEL | 1 SEC ~ 60SEC | |
| | NIGHT BURST | ON/OFF | |
| | INITIAL SET | | |
| | PREVIOUS | | |
| DAY | | | |
| NIGHT | | | |
| EXT | | | |

5. WDR/BLC/ECLPS

| | | | |
|---------|--------------|------------------------|--|
| WDR | WDR LEVEL | (HIGH / LOW / MIDDLE) | WDR (Wide Dynamic Range) - used this functions when used indoors and when the camera is pointing towards the windows or entrances. BLC Level: use this function to enhance the brightness on the |
| BLC | BLC LEVEL | (HIGH / LOW / MIDDLE) | |
| ECLIPSE | ECLIPSE MENU | | |
| | AREA SETTING | OFF OFF OFF OFF | |
| | | OFF OFF OFF OFF | |
| | | OFF OFF OFF OFF | |
| | ALL AREA SET | ON/OFF | |
| | MASK COLOR | GRAY / D. GRAY / BLACK | |
| | | | |

| | |
|--------------|--------|
| ECLPS LEVEL | (1~5) |
| GAIN CONTROL | ON/OFF |

Enhance the brightness on the image.

Eclipse: this is used to block a heavily bright light as from the cars headlights

Use the **Area setting** to block lights in sections of the screen and also has a option for a **ALL AREA SET**. Choose between 3 colors for the Mask. **Eclps Level** to adjust the size of the Blocking Mask

6. WHITE BAL.

| | | |
|----------|------------|------------------|
| COL-ROLL | | |
| PUSH | | |
| ATW | | |
| MANUAL | COLOR TEMP | INDOOR / OUTDOOR |
| | RED | (1~100) |
| | BLUE | (1~100) |

COL-ROLL

PUSH adjust the white balance at the push of the button.

ATW (Auto Tracing White Balance)

Manual - Adjust your setting to indoor or outdoor and also the

7. 3D-DNR

| | | |
|-----|-----------------|----------|
| OFF | | |
| ON | 3D-DNR MENU | |
| | DNR LEVEL | (1~63) |
| | DESTINATION | (1~63) |
| | GLOBAL MOVEMENT | (ON/OFF) |

3D-DNR (digital Noise Reduction)

DNR LEVEL

8. EFFECTS

| | |
|--------------|--------------------------------|
| D.ZOOM MODE | ON/OFF |
| IMAGE FREEZE | ON/OFF |
| D-EFFECT | V-FLIP / MIRROR / ROTATE / OFF |
| COLOR | ON/OFF |
| CONTRAST | (1~100) |
| SHARPNESS | (1~100) |
| CR GAIN | (-100 / 0 / +100) |
| CB GAIN | (-100 / 0 / +100) |
| INITIAL SET | |
| PREVIOUS | |

Effects:

D. Zoom - Select from Digital zoom on or OFF.

D-Effect - Changes the picture from normal to Vertical Flip / mirror / Rotate / OFF.

Color - Select between color or B/W image.

Contrast - adjusts the contrast of the camera

Sharpness - Adjusts the Sharpness of the camera

CR Gain - RED color Gain adjustment

CB Gain - BLUE Color Gain

CB Gain - BLUE COLOR Gain Adjustment

9. SPECIAL

| | | |
|---------------|---|--------------------------------|
| MOTION DET. | ON/OFF | |
| PRIVACY MASK | ON/OFF | |
| LANGUAGE | ENGLISH / KOREAN / RUSSIAN / SPANISH / FRENCH | |
| STABILIZER | ON/OFF | |
| L/L SYNC | INT | |
| MONITOR TYPE | CRT / LCD | |
| FACTORY RESET | | |
| COMM SETTINGS | PROTOCOL | PELCO-D |
| | CAMERA ID | CAMERA ID (0~250) |
| | | DISPLAY ID ON / OFF |
| | | ID POSITION MOVE AND PRESS SET |
| | | BAUDRATE 4800~57600 |
| | | SAVE / REBOOT |
| | | PREVIOUS |

Privacy Mask - Blocks parts of the screen for privacy.
Language - Select between a list of the Languages available on list.
Monitor Type - Select the type of monitor used for this camera.
COMM Settings - this camera is set o a fixed PELCO-D Protocol and selectable ID (0~250)
Display ID - ON / OFF to display the Camera ID
ID Position - can be set along the top part of the screen from far left to far right.
Baudrate - selectable from 4800 up to 57600

10. EXIT